

TRS Multi Carrier RF Amplifier

HD29611

806 – 821 MHz / 2 Watts

Product Features

- Multi carrier power amplifier
- Solid State power amplifier
- High linearity and high efficiency
- 50 ohms input / output impedance

Application

- TRS Repeater

1. Electrical Specification.



Parameter	Specification	Remark
Frequency Range	806MHz~821MHz	15MHz BW
Output Power	2W	ALC 2.5W : Min 10dB
Gain	52dB±1dB	
Gain Flatness	±0.5dB	
Gain Variation Over Temp.	±1dB max	-20°~+60°
IMD	< -60dBc	CW 10 tone, Ch Sp. : 25kHz
Harmonic	-45dBc max	
Input VSWR	1.5:1 max.	
Output VSWR	1.5:1 max.	Isolator Applied
Normal Operating Voltage	+27V	
DC Current Consumption	1.5A max.	@2W
Output protection	Isolator	
Shut-down Temp Level	90±5°	70±5° Auto Enable

2. Environmental Specification

Parameter	Specification	Remark
Operating Temperature	-20°~+60°	
Storage Temperature	-40°~+85°	
Relative Humidity	0%~90%	Non-condensing

3. Mechanical Specification.

Physical Dimension : 120mm X 150mm X 28mm

TRS Multi Carrier RF Amplifier

HD29611

806 – 821 MHz / 2 Watts

4. Pin Assignment

I/O Interface (D-Sub 9Pin Male)	1.	+27V_IN	
	2.	+27V_IN	
	3.	En/Disable Control	High (Disable) Open & Low (Enable)
	4.	GND_IN	
	5.	GND_IN	
	6.	Over Power Alarm	35dBm
	7.	VSWR Alarm	30dBm(Output Open)
	8.	High Temp. Alarm	High (shut-down) Low (Normal) Alarm & Shutdown +90°↑ Auto Recovery +70°↓
	9.	FWD Power Monitor	4V / 33dBm
DC INPUT Connector (D-Sub 9Pin Male)	1,2		+27V
	4,5		GND



TRS Multi Carrier RF Amplifier

HD29611

806 – 821 MHz / 2 Watts

5. Electrical Test Data

5.1 IMD @Po=+33dBm(CW 10 Tone / CW 2 Tone) / DC 27V, 1.2A



TRS Multi Carrier RF Amplifier

HD29611

806 – 821 MHz / 2 Watts

6. Outline Drawing

